

UNIpower™

SA ASSEMBLED GENERATOR SETS PETROL DRIVEN

- HEAVY DUTY
- SA ASSEMBLED
- IDEAL FOR CONTRACTOR USE
- BUILT TO LATEST SANS SAFETY SPECIFICATIONS
- FITTED WITH EARTH LEAKAGE FOR AC POWER
- FULL SPARE PARTS BACK UP



Model	Uni SA 6.0 P	UNI SA 7.0 P	Uni SA 7.0/3 P
Output max. - kw /kva	6.0	7.0	7.0/3
Engine size - hp	13.0	15	15.0
AC Output	230v	230v	380v
Power outlets	2 x 230V	2 x 230V	1 x 380v/1 x 220v
Regulation method	Compound regulation	Compound regulation	AVR
Earth leakage fitted	Yes	Yes	No
Circuit breaker fitted	Yes	Yes	Yes
Power factor cos	F 1	F 1	F 1
Frequency ≤	50 hz	50 hz	50 hz
Engine speed RPM	3000	3000	3000
Starting method	Recoil or electric	Recoil or electric	Recoil or electric
12v DC charging	yes	yes	yes
Fuel tank capacity - L	5.7	5.7	5.7
Dry weight - kg (approx.)	120	125	130
Size - L x W x H	800 x 520 x 600	800 x 520 x 600	800 x 520 x 600



HEAD OFFICE

Tel: 011 824 0410
Fax: 011 824 0427

WADEVILLE

Tel: 011 824 0410
Fax: 011 824 0427

CAPE TOWN

Tel: 021 511 1126
Fax: 021 511 1215

DURBAN

Tel: 031 902 7595
Fax: 031 902 7620

WITBANK

Tel: 013 697 3450/1
Fax: 013 697 3452

MOSSEL BAY

Tel: 044 601 2850
Fax: 044 601 2850

RICHARDS BAY

Tel: 035 751 1965
Fax: 035 751 1566

RUSTENBURG

Tel: 014 592 1667
Fax: 014 592 2703

SASOLBURG

Tel: 016 976 0485
Fax: 016 973 2399

SECUNDA

Tel: 017 610 5289
Fax: 017 610 5289

PORT ELIZABETH

Tel: 041 453 1090
Fax: 041 453 1093

LEPHALLE

Tel: 014 763 4150
Fax: 014 763 2639